

WIRELESS SYNCHRONOUS TIME SYSTEM

Background and Summary of the Invention

The present invention relates to synchronous time systems and particularly to systems having "slave" devices synchronized by signals transmitted by a controlling
5 "master" device. More particularly, the present invention relates to synchronous time systems, wherein the master device wirelessly transmits the signals to the slave devices.

Conventional hard-wired synchronous time systems (for example clock or bell systems, etc.) are typically used in schools and industrial facilities. The devices in these systems are wired together to create a synchronized system. Because of the extensive
10 wiring required in such systems, installation and maintenance costs may be high.

Conventional wireless synchronous time systems are not hard-wired, but instead rely on wireless communication among devices to synchronize the system. For example, one such system utilizes a government WWVB radio time signal to synchronize a system of clocks. This type of radio controlled clock system typically includes a master unit that
15 broadcasts a government WWVB radio time signal and a plurality of slave clocks that receive the time signal. To properly synchronize, the slave clock units must be positioned in locations where they can adequately receive the broadcast WWVB signal. Interference generated by power supplies, computer monitors, and other electronic equipment may interfere with the reception of the signal. Additionally, the antenna of a radio controlled
20 slave clock can be de-tuned if it is placed near certain metal objects, including conduit, wires, brackets, and bolts, etc., which may be hidden a building's walls. Wireless synchronous time systems that provide reliable synchronization and avoid high installation and maintenance costs would be welcomed by users of such systems.

According to the present invention, a wireless synchronous time system comprises
25 a primary event device or "master" device including a first receiver operable to receive a

global positioning system ("GPS") time signal, and a first processor coupled to the first receiver to process the GPS time signal. The primary event device also includes a memory coupled to the first processor and operable to store a programmed instruction, including a preprogrammed time element and a preprogrammed function element. The primary event
5 device also includes an internal clock coupled to the first processor to store the time component and to increment relative to the stored time component thereafter to produce a first internal time. A transmitter is also included in the primary event device and is coupled to the first processor to transmit the first internal time and the programmed instruction.

10 The synchronized event system further includes a secondary event device or "slave" device having a second receiver to wirelessly receive the first internal time and the programmed instruction, which are transmitted by the primary event device. The secondary event device includes a second processor coupled to the second receiver to selectively register the programmed instruction, a second internal clock coupled to the
15 processor to store the time component and to increment relative to the stored time component thereafter to produce a second internal time, and an event switch operable to execute the registered programmed instruction when the second internal time matches the preprogrammed time element of the programmed instruction.

In preferred embodiments, the secondary event device or "slave" device may
20 include an analog clock, a digital clock, a time-controlled switching device (e.g., a bell, a light, etc.), or any other device for which the time and functionality need to be synchronized with other devices. In these devices, the programmed instruction includes an instruction to display time and/or an instruction to execute a predetermined timed function. The programmed instruction is broadcast to the "slave" unit devices by the primary event
25 device or "master" device. In this way, for example, the master device synchronizes the

time displayed by a system of analog slave clocks, synchronously sounds a system of slave bells, synchronizes the time displayed by a system of slave digital clocks, or synchronizes any other system of devices for which a time and/or functionality are desired to be synchronized.

5 In preferred embodiments, these systems further include a power interrupt module coupled to the processors to retain the internal time and the programmed instruction in the event of a power failure. Both the "master" primary event device and the "slave" secondary event device are able to detect a power failure and store current time information into separate memory modules.

10 The system is synchronized by first receiving a GPS time signal at the master device and setting a first internal clock to the GPS time signal. The first internal clock is then incremented relative to the GPS time signal to produce a first internal time. Operational data in the form of the programmed instruction, including the preprogrammed time element and the preprogrammed function element, is then retrieved from a memory
15 and is wirelessly transmitted along with the first internal time. A second receiver at the "slave" device wirelessly receives the first internal time and the operational data and selectively registers it. A second internal clock within the "slave" device is set to the first internal time and is incremented relative thereto to produce a second internal time. In preferred embodiments, such as an analog clock, the second internal time is simply
20 displayed. In other slave devices, such as a system of bells, a function is identified from the preprogrammed function element and is executed (for example, the bells are rung) when the second internal time matches the preprogrammed time element.

 Additional features and advantages will become apparent to those skilled in the art upon consideration of the following detailed description of preferred embodiments
25 exemplifying the best mode of carrying out the invention as presently perceived.

Brief Description of the Drawings

The detailed description particularly refers to the accompanying Figures in which:

Fig. 1 shows a block diagram of a wireless synchronous time system according to
5 the present invention including a master device which receives a GPS signal and
broadcasts a time and programmed instruction to a system of slave devices;

Fig. 2 shows a block diagram of the master device of Fig. 1;

Fig. 3A shows a time package structure used in the transmission of the time
element of Fig. 1;

10 Fig. 3B shows a function package structure used in the transmission of the
programmed instruction element of Fig. 1;

Fig. 4 shows a block diagram of an analog clock slave device of Fig. 1;

Fig. 4A shows a clock movement box used in the setting of the slave clock of Fig.
4;

15 Fig. 5 shows a block diagram of a slave device of Fig. 1, which includes a switch
for controlling the functionality of the device; and

Fig. 6 shows a flow chart illustrating the functionality of a wireless synchronous
time system in accordance with the present invention.

20 **Detailed Description of the Drawings**

Referring to Fig. 1, a wireless synchronous time system 100 in accordance with the
present invention includes a primary "master" device 110, which receives a first time
signal through a receiving unit 115 and broadcasts a second time signal to a plurality of
"slave" secondary event devices 130. The receiving unit 115 includes a GPS receiver 127
25 having an antenna 129 which receives a global positioning system ("GPS") signal,

including a GPS time signal component. The receiving unit 115 sends the GPS time signal component to the primary master device 110 where it is processed, as further discussed below.

The primary master device 110 further includes a transmission unit 120, which
5 wirelessly transmits a signal to the secondary or "slave" devices 130. The signal sent to the slave devices 130 includes the processed GPS time signal component and/or a programmed instruction which is input to the primary master device 110 through a programmer input connection 125. The programmed instruction includes a
10 preprogrammed time element and a preprogrammed function element which, along with the GPS time signal component, is used by the primary master device 110 to synchronize the slave devices 130. The processed GPS time signal component and the programmed instruction are wirelessly transmitted to the slave devices 130 at approximately a frequency between 72 and 76 MHz.

As shown in Fig. 1, examples of secondary or slave devices 130 include an analog
15 time display 145, a digital time display 135, and a switching device 140, which may be associated with any one of a number of devices, such as a bell, a light, or a lock, etc. Each of the secondary devices 130 includes an antenna 150 to wirelessly receive the processed GPS time signal component and the programmed instruction from the primary master device 110. Each of the secondary devices 130 also includes a processor (see Fig. 4,
20 element 410 and Fig. 5, element 525, not shown in Fig. 1) to process processed time signal and the programmed instruction received from the master device. As will be further discussed below, when the preprogrammed time element of the programmed instruction matches a second time generated by the slave device, an event will be executed.

For the analog time display 145, shown in Fig. 1, the event will include positioning
25 an hour, minute, and second hand to visually display the current time. For the digital time

display 145, the event will include digitally displaying the current time. For the time controlled switching device 140, the event may include any of a number of events which may be controlled by the switch. For example, a system of bells may include switches which sound the bells at a particular time. Alternatively, a system of lights may include switches which turn the lights on or off at a particular time. It will be readily apparent to those of ordinary skill in the art that the slave devices may include any one of a number of electronic devices for which a particular functionality is desired to be performed at a particular time, such as televisions, radios, electric door locks, etc.

Referring to Fig. 2, a detailed diagram of the primary master device 110 is shown.

10 The primary master device 110 receives the GPS time signal component from the receiving unit 115 (Fig. 1) at a GPS time signal input receiving unit or connector 205. The primary master device 110 further includes a processor 210, a memory 215, a programmer input connector 125, a display 225, a transmission unit 120, and a powered input socket 235. These elements of the primary master device 110 serve to receive, process, and
15 transmit the information used to synchronize the slave units 130, as will be fully discussed below. Additionally, a channel switch 245, time zone switch 250, and a daylight savings bypass switch 255 are included in the primary master device 110. Lastly, the primary master device 110 includes a power interrupt module 258 coupled to the processor 210 to retain the internal time and the programmed instruction in the event of a power loss.

20 Upon powering up the master device 110, the processor 210 checks the setting of the channel switch 245, the time zone switch 250, and the daylight savings bypass switch 255. The processor 210 stores the switch information into the memory 215. A GPS signal is received through the GPS signal antenna 129 and a GPS time signal component is extracted from it. When the receiving unit or connector 205 receives the GPS time signal
25 component, the processor 210 adjusts it according to the switch information of the channel

switch 245, the time zone switch 250, and the daylight savings bypass switch 255, and sets an internal clock 260 to the processed GPS time signal component to produce a first internal time.

The channel switch 245 enables a user to select a particular transmission frequency
5 determined best for transmission in the usage area, and to independently operate additional primary master devices in overlapping broadcast areas without causing interference between them. The GPS time signal uses a coordinated universal time ("UTC"), and requires a particular number of compensation hours to display the correct time and date for the desired time zone. The time zone switch 250 enables the user to select a desired time
10 zone, and permits a worldwide usage. Lastly, the GPS time signal may not include daylight savings time information. As a result, users in areas that do not require daylight savings adjustment will be required to set the daylight savings bypass switch 255 to bypass an automatic daylight savings adjustment program. Manual daylight savings time adjustment can be accomplished by disconnecting the power source (not shown) from the
15 power input socket 235, adjusting the time zone switch 250 to the desired time zone and reconnecting the power source to the power input socket 235.

Once the processor 210 adjusts the GPS time signal component according to the settings of the switches discussed above and sets the internal clock 260 to produce the first internal time, the internal clock 260 starts to increment the first internal time until another
20 GPS time signal is received from the GPS receiver 127 (Fig. 1). Between receiving GPS time signals, the internal clock 260 independently keeps the first internal time which, in addition to date information and reception status, is displayed on the display 225. In addition to processing the time signal, the processor 210 also checks for a new programmed instruction on a continuous basis, and stores any new programmed
25 instruction in the memory 215. As briefly mentioned above, to enter a programmed

instruction, a user keys in the programmed instruction into a computing device (e.g., a personal computer, a PDA, etc.) and transfers the programmed instruction to the primary master device 110 through the programmer input connector 125. The programmed instruction is stored in the memory 215 and, along with the first internal time kept in the internal clock 260, is transmitted through the transmission unit 120 at the transmission frequency set in the channel switch 245.

The first internal time and the programmed instruction are transmitted by the master device 110 using a data protocol as shown in Figs. 3A and 3B. Fig. 3A shows a time packet structure 300 comprising of preprogrammed time element, and having a 10-bit preamble 304, a sync bit 308, a packet identity byte 312, an hour byte 316, a minute byte 320, a second byte 324, a checksum byte 328 and a postamble bit 332. Fig. 3B shows a function packet structure 350 comprising a preprogrammed function element, and having a 10-bit preamble 354, a sync bit 358, a packet identity byte 362, an hour byte 366, a minute byte 370, a function byte 374, a checksum byte 378, and a postamble bit 382. Each secondary slave device 130 will receive the signal broadcast by the master device 110 and including information according to the time packet structure of Fig. 3A and the function packet structure Fig. 3B. The secondary slave device will try to match the packet identity bytes 312 or 362 with an internal identity number programmed in its processor (i.e., 410 of Fig. 4 or 525 of Fig. 5) to selectively register the program instruction. It should be readily apparent to those of ordinary skill in the art that the time packet structure 300 and the function packet structure 350 may have a different structure size so that more or less information may be transmitted using these packets. For example, the time packet structure may include, in addition to the existing timing bytes, a month byte, a day byte, a year byte, and a day of the week byte. Similarly, the function packet structure 350 may

include additional hour, minute, and function bytes to terminate the execution of an event triggered by the hour, minute, and function bytes 366, 370, and 374, shown in Fig. 3B.

Referring to Fig. 4, a diagram of the analog slave clock 145 of Fig. 1 is shown.

The slave clock 145 includes a second receiving unit 402 having an antenna 150 and a
5 second receiver 406. The slave clock 145 also includes a second processor 410, a second
memory 415, a second internal clock 420 and an analog display 425, including a set of
hands 430 including a second hand 432, a minute hand 434, and an hour hand 436. As
with the master device 110, the secondary slave clock 145 also includes a power interrupt
module 438 coupled to the processor 410 to retain an internal time and a programmed
10 instruction in the event of a power loss to the slave clock 145.

Fig. 4A illustrates a clock movement box 450 having a manual time set wheel 465,
and a push button 470 for setting the position of the hands 430 of the analog display 425.
The clock movement box 450 is of the type typically found on the back of conventional
analog display wall clocks, and is used to set such clocks. In setting the analog slave clock
15 145, the manual time set wheel 465 of the clock movement box 450 is initially turned until
the set of hands 430 shows a time within 29 minutes of the GPS time (i.e., the actual time).
When power is applied to the slave analog clock 145, the second hand 432 starts to step.
The push button 470 of the clock movement box 450 is depressed when the second hand
reaches the 12 o'clock position. This signals to the second processor 410 that the second
20 hand 432 is at the 12 o'clock position, enabling the second processor 410 to "know" the
location of the second hand 432. The push button 470 is again depressed when the second
hand 432 crosses over the minute hand 434, wherever it may be. This enables the second
processor 410 to "know" the location of the minute hand 434 on the clock dial. (See U.S.
Patent Application No. 09/645,974 to O'Neill, the disclosure of which is incorporated by
25 reference herein).

To synchronize itself to the master device 110, the second receiver 406 of the slave device 145 automatically and continuously searches a transmission frequency or a channel that contains the first internal time and the programmed instruction. When the receiving unit 402 wirelessly receives and identifies the first internal time, the processor 410 stores
5 the received first internal time at the second internal clock 420. The second internal clock 420 immediately starts to increment to produce a second internal time. The second internal time is kept by the second internal clock 420 until another first internal time signal is received by the slave clock 145. If the processor 410 determines that the set of hands 430 displays a lag time (i.e., since a first internal time signal was last received by the slave
10 clock 145, the second internal clock 420 had fallen behind), the processor 410 speeds up the second hand 432 from one step per second to eight steps per second until both the second hand 432 and the minute hand 434 agree with the newly established second internal time. If the processor 410 determines that the set of hands 430 shows a lead time (i.e., since the first internal time signal was last received by the slave clock 145, the second
15 internal clock 420 had moved faster than the time signal relayed by the master device), the processor 410 slows down the second hand 432 from one step per second to one step per five seconds until both the second hand 432 and the minute hand 434 agree with the newly established second internal time.

In additional to slave clocks which simply display the synchronized time signal, a
20 slave device 130 may include the switching slave device 140 depicted in Fig. 5. Instead of simply displaying the time signal, the switching slave device 140 utilizes the time signal to execute an event at a particular time. In this way, a system of slave switching devices can be synchronized. The slave switching device 140 includes a second receiving unit 510 having an antenna 150 and a second receiver 520, a second processor 525, a second
25 internal clock 530, a second memory 535, an operating switch 540, and a device power

source 550. The secondary slave switching device 140 further includes a power interrupt module 552 coupled to the processor 410 to retain the internal time and the programmed instruction on a continuous basis, similar to the power interrupt module of the master device 110 and the slave clock 145. The secondary slave switching device 140 includes
5 any one of a number of devices 555, which is to be synchronously controlled. Depending upon the device 555 to be controlled, a first end 560 of the device is coupled to a normally open end ("NO") 565 or a normally closed end ("NC") 570 of the operating switch 540. The first power lead 575 of the device power source 550 is then coupled to a second end 580 of the device 555, while a second power lead 585 of the device power source 550 is
10 coupled to the normally open end 565 or the normally closed end 570 of the operating switch 540 to complete the circuit.

Like the receiver 406 of the slave clock 145, the second receiver 520 of the slave switching device 140 automatically searches a transmission frequency or a channel that contains a first internal time and a programmed instruction from the master device 110.
15 When the receiving unit 510 wirelessly receives and identifies the first internal time, the second processor 525 stores the received first internal time in a second internal clock 530. The second internal clock 530 immediately starts to increment to produce a second internal time until another first internal time signal is received from the master device 110. Additionally, the programmed instruction is stored in the memory 535. When there is a
20 match between the second internal time and the preprogrammed time element of the programmed instruction, the preprogrammed function element will be executed. For example, if the preprogrammed time element contains a time of day, and the preprogrammed functional element contains an instruction to switch on a light, the light will be switched on when the second internal clock 530 reaches that time specified in the
25 preprogrammed time element of the programmed instruction.

Referring to Fig. 6, a flow chart 600 illustrates a wireless synchronous time system according to the present invention. The flow chart 600 illustrates the steps performed by a wireless synchronous time system according to the present invention for any number of systems of slave devices. The process starts in a receiving step 610 where a master device
5 receives a GPS time signal. As indicated in the flow chart at step 610, the master device will continuously look for and receive new GPS time signals. Next, at step 615 a first internal clock is set to the received GPS time. Next, the first internal clock will start to increment a first internal time in step 620. In a parallel path, at step 625, the master device receives programmed instructions input by a user of the system. Again, the flow chart
10 indicates that the master device is able to continuously receive programmed instruction so that a user may add additional programmed instructions to the system at any time. As discussed above, the programmed instructions will include a preprogrammed time element and a preprogrammed function element. The programmed instruction is then stored in a first memory at step 627. Next, when preset periodic times are reached at step 629, the
15 programmed instruction is retrieved at step 630 and transmitted at step 632 to the slave device along with the first internal time at step 635. In other words, when the first internal clock reaches particular preset times (e.g., every five minutes) the programmed instruction and the first internal time are wirelessly transmitted to the slave devices.

The programmed instruction and/or the first internal time are received at the slave
20 device in step 640. If the slave device is to merely synchronously display a time, such as a clock, but does not perform any functionality, there is no need to receive the programmed instruction. In slave devices such as bells, lights, locks, etc., in addition to the first internal time, at step 642, the processor will select those programmed instructions where the packet identity byte matches with the slave devices identity. The selected programmed
25 instruction is then stored or registered in the memory at the secondary slave device in step

645. A second internal clock is then set to the first internal time at step 650 to produce a second internal time. In step 655, like the first internal clock, the second internal clock will start to increment the second internal time. The second internal time is displayed at step 655. Meanwhile, a function is identified from the preprogrammed function element at
5 step 670. When the second internal time has incremented to match the preprogrammed time element at step 675, the function will be executed in step 680. Otherwise, the secondary slave device will continue to compare the second internal time with the preprogrammed time element until a match is identified.

It will be readily understood by those of ordinary skill in the art, that both the first
10 internal clock and the second internal clock increment, and thus keep a relatively current time, independently. Therefore, if, for some reason, the master device does not receive an updated GPS time signal, it will still be able to transmit the first internal time. Similarly, if, for some reason, the slave device does not receive a signal from the master device, the second internal clock will still maintain a relatively current time. In this way, the slave
15 device will still display a relatively current time and/or execute a particular function at a relatively accurate time even, if the wireless communication with the master device is interrupted. Additionally, the master device will broadcast a relatively current time and a relatively current programmed instruction even if the wireless communication with a satellite broadcasting the GPS signal is interrupted. Furthermore, the power interrupt
20 modules of the master and slave devices help keep the system relatively synchronized in the event of power interruption to the slave and/or master devices.

It is to be understood that the invention is not limited in its application to the details of construction and the arrangement of components set forth in the above description or illustrated in the drawings. The invention is capable of other embodiments
25 and of being practiced or being carried out in various ways. Also, it is to be understood

that the phraseology and terminology used herein is for the purpose of description and should not be regarded as limited. The use of "including" and "comprising" and variations thereof herein is meant to encompass the items listed thereafter in accordance thereof as well as additional items. Although the invention has been described in detail with

5 reference to certain preferred embodiments, variations and modifications exist within the scope and spirit of the invention as described and defined in the following claims.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
22